



AURIGA Paypass 7/22kW

- Tap and go- Paypass interface
- Type 2 Untethered compatible with all makes and models of EVs in Australia
- Variable charge rates from 6A to 32A single or three phase
- Can be installed by any electrician
- Paid charging ready to go out the box

Easy to use, plug and pay interface

1. Pull up to the charging bay and plug in
2. Select time to charge up (in 30 minute increments)
3. Tap card or phone to initiate the charging session.

PayPass Tap & Go Features:

- Simple, familiar user interface & experience
- Full usage and billing data
- Remote vending / override
- Instant refunds
- Anti-fraud thresholds
- Real-time data/DEX
- 3G / 4G LTE / Ethernet
-

AURIGA PAYPASS 7/22KW SPECIFICATIONS



	Model	7/22kW
AC Input	7kW Input Rating 22kW Input Rating AC Input Connection	PE 230 VAC +/- 10% PE 400 VAC +/- 10% 3P + N + PE, Wye connection
	Max. Input Current	40A
	Frequency	50/ 60 Hz
	Power Factor	>0.99 @ full load
	Efficiency	95%
User Interface	TFT-LCD Touch Panel Push Buttons Interface	3" LCD Display Emergency Stop Wi-Fi, RJ45, 4G
Packing	Dimension Weight Operating Temperature	130H x 240W x 240D 25kg -25 - +45 degrees celsius
Environmental	Humidity Altitude IP Level Cable Length	5% ~ 90% RH, non-condensing 2000m IP67/ IK10 N/A (Untethered)
Mechanical Regulation	Certification Charging Protocol	IEC61851-1 CE, ROHS, RCM SO15118
Safety & Compliance	Compliance DC leakage detection Protection	IEC 62196-2, IEC 61851-22 RCM 6mA DC residual current monitor Over/under voltage, over current, over temperature, ground fault